# Altronix® PD16W, PD16WCB UL Recognized Power Distribution Modules

Rev. DSPD16W/CB - K08F



### **Overview**

• These power distribution modules, are designed to convert a single AC or DC input into sixteen (16) individual outputs.

#### PD16W

- Converts a single AC or DC input into sixteen (16) individual fuse protected outputs.
- Fuses rated @ 3.5 amp/250V.

#### PD16WCB

- Converts a single AC or DC input into sixteen (16) individual Class 2 Rated PTC protected power limited outputs.
- PTC's are rated @ 2.5 amp.

# **Specifications**

- 24VAC or 28VAC up to 12.5 amp, 12 or 24VDC up to 10 amp. (total output current should not exceed max current rating of power supply employed).
- Power on green LED indicator.

# **Board Dimensions (approximate)**

6"H x 5.875"W x .95"D

# **Mounting Diagram**

